

Total No. of Questions : 8]

[Total No. of Printed Pages : 3

Roll No .....

**EE/EX-3005-CBGS**

**B.E., III Semester**

Examination, December 2020

**Choice Based Grading System (CBGS)**

**Signals and Systems**

*Time : Three Hours*

*Maximum Marks : 70*


- Note:** i) Attempt any five questions.  
ii) All questions carry equal marks.  
iii) Sketch neat diagram.

1. a) Write short notes on followings:  
i) Periodic and non-periodic signals  
ii) Power and energy signals  
iii) Discrete time impulse function  $\delta(n)$   
b) A continuous time signal given below. Sketch the following signals.

i)  $\delta\left[4 - \left(\frac{t}{2}\right)\right]$

ii)  $[\delta(t) + \delta(-t)]u(t)$

iii)  $\delta(2t + 1)$



2. a) Discuss the determination of the Fourier series representation of continuous time periodic signals.  
b) Determine the fundamental frequency  $\omega_0$  and continuous-time Fourier series coefficient  $A_K$  for the signal.

$$\delta(t) = 2 + \cos\left(\frac{2\pi}{3}t\right) + 4 \sin\left(\frac{5\pi}{3}t\right)$$

EE/EX-3005-CBGS

PTO

[2]

3. a) List and explain various properties of Fourier transform.  
b) What do you understand by region of convergence (ROC)? Explain with example.
4. a) Find Fourier transform of  
i)  $t \cos at$   
ii)  $\text{sgn}(t)$   
b) Calculate the Laplace transform of the following.  
i)  $t \sin at$   
ii)  $te^{-2t}$   
iii)  $t^n$
5. a) State and prove time shifting and differentiation in the Z-domain property of Z-transform.  
b) Determine the causal signal  $x(n)$  whose Z-transform is given by

i) 
$$x(z) = \frac{1+z^{-1}}{1-z^{-1}+0.5z^{-2}}$$

ii) 
$$x(z) = \frac{1}{(1+z^{-1})(1-z^{-1})^2}$$

6. a) Determine the response of the system

$$y(n) = \frac{5}{6}y(n-1) - \frac{1}{6}y(n-2) + x(n)$$

to the input signal  $x(n) = \delta(n) - \frac{1}{3}\delta(n-1)$

- b) State and prove convolution property of Z-transform.

[3]

7. a) If the unit step response of a system starting from rest is given by  $s(t) = 3(1 - e^{-st}), t \geq 0$ . Then find the transfer function of the system.
- b) If  $x(n) \{1, 5, -2, 1, \underset{\uparrow}{3}, 4, 2, 0, 5\}$  then find DTFT  $[x(e^{j\omega})]$ .
8. Write short notes on the following.
- Classification of continuous and discrete time signals
  - Linear time invariant systems and properties
  - Fourier series analysis

\*\*\*\*\*